Series EV18






AVENTICS™ Series EV18



E/P pressure regulator, Series EV18

- Pressure supply, right, Display: display
- Qn = 16500 l/min
- Compressed air connection output G 1 G 3/4
- Electr. connection M12, 5-pin, A-coded
- serial control IO-Link
- Pilot valves





Technical data

| Version | Poppet valve |
|-------------------------------|-----------------------|
| Working pressure max | 11 bar |
| Ambient temperature min./max. | 0 50 °C |
| Medium temperature min./max. | 0 50 °C |
| Max. particle size | 50 µm |
| Oil content of compressed air | 0 5 mg/m ³ |
| Nominal flow Qn | 16500 l/min |
| DC operating voltage | 24 V |
| Voltage tolerance DC | -20% / +30% |
| Hysteresis | 0.12 bar |
| Permissible ripple | 5% |
| Max. power consumption | 220 mA |
| Weight | 2.15 kg |

| Part No. | Pressure setting range min./max. | Compressed air connection Input |
|------------|----------------------------------|------------------------------------|
| R414011411 | 0 10 bar | G 1 |
| R414011412 | 0 10 bar | G 1 |
| R414011414 | 0 10 bar | G 1 |
| R414011417 | 0 10 bar | G 3/4 |
| R414011418 | 0 10 bar | G 3/4 |
| R414011420 | 0 10 bar | G 3/4 |

| Part No. | Compressed air connection | Nominal input value | Actual output value | serial control |
|------------|---------------------------|---------------------|---------------------|----------------|
| | Output | Min./max. | Min./max. | |
| R414011411 | G 1 | 0 10 V | 0 10 V | - |
| R414011412 | G 1 | 4 20 mA | 4 20 mA | - |
| R414011414 | G 1 | - | - | IO-Link |
| R414011417 | G 3/4 | 0 10 V | 0 10 V | - |
| R414011418 | G 3/4 | 4 20 mA | 4 20 mA | - |
| R414011420 | G 3/4 | - | - | IO-Link |

Page 3 | AVENTICS



The min. control pressure must be adhered to, since otherwise faulty switching and valve failure may result! The pressure dew point must be at least 15 °C under ambient and medium temperature and may not exceed 3 °C .

The oil content of compressed air must remain constant during the life cycle.

Use only the approved oils from AVENTICS. Further information can be found in the "Technical information" document (available in the MediaCentre).


Power outage: maintain pressure

Technical information

| Material | |
|------------|--------------------------|
| Housing | Polyamide |
| Base plate | Aluminum |
| Seals | Nitrile butadiene rubber |

Dimensions


Dimensions



1) Connection thread

EMERSON


Pressure supply, righ



EMERSON.

Diagrams

Flow characteristic curve




p1 = Working pressure

p2 = Secondary pressure

qn = Nominal flow

Circuit diagram

Characteristic curve and plug assignment for IO-Link version




1) power supply

2) C/Q Line (pin 4) Not connected (NC) (pin 2) are related to 0 V (pin 3).

3) The power supply must be protected by an external M 0.5 A fuse.



Characteristic and pin assignment for current control with actual output value



1) power supply


2) Actual value (pin 4) and nominal value (pin 2) are related to 0 V (pin 3).

Nominal input value (ohmic load 100 Ω), actual output value: external ohmic load 300 Ω . If the power supply is switched off, the nominal input value is high-ohmic.

3) The power supply must be protected by an external M 0.5 A fuse.

Connect the plug via a shielded cable to ensure EMC.

Characteristic and pin assignment for voltage control with actual output value



1) power supply


2) Actual value (pin 4) and nominal value (pin 2) are related to 0 V (pin 3).

Nominal input value (R = 1 M Ω), actual output value: min. load resistance > 10 K Ω . If the power supply is switched off, the nominal input value is high-ohmic.

3) The power supply must be protected by an external M 0.5 A fuse.



Functional diagram




a) Voltage supply

b) Nominal value

c) Actual output value

Functional diagram, IO-Link




a) Supply Voltage

b) C/Q Line

Pin assignments

Plug assignment



1) 24 V DC

- 2) Nominal input value
- 3) GND
- 4) Actual output value

5) Ground






E/P pressure regulator, Series EV18

- Pressure supply, left, Display: display
- Qn = 16500 l/min
- Compressed air connection output G 1 G $3\!/\!4$
- Electr. connection M12, 5-pin, A-coded
- serial control IO-Link
- Pilot valves





Technical data

| Version | Poppet valve |
|-------------------------------|-----------------------|
| Working pressure max | 11 bar |
| Ambient temperature min./max. | 0 50 °C |
| Medium temperature min./max. | 0 50 °C |
| Max. particle size | 50 µm |
| Oil content of compressed air | 0 5 mg/m ³ |
| Nominal flow Qn | 16500 l/min |
| DC operating voltage | 24 V |
| Voltage tolerance DC | -20% / +30% |
| Hysteresis | 0.12 bar |
| Permissible ripple | 5% |
| Max. power consumption | 220 mA |
| Weight | 2.15 kg |

| Part No. | Pressure setting range | Compressed air connection |
|------------|------------------------|---------------------------|
| | min./max. | Input |
| R414011409 | 0 10 bar | G 1 |
| R414011410 | 0 10 bar | G 1 |
| R414011413 | 0 10 bar | G 1 |
| R414011415 | 0 10 bar | G 3/4 |
| R414011416 | 0 10 bar | G 3/4 |
| R414011419 | 0 10 bar | G 3/4 |

| Part No. | Compressed air connection | Nominal input value | Actual output value | serial control |
|------------|---------------------------|---------------------|---------------------|----------------|
| | Output | Min./max. | Min./max. | |
| R414011409 | G 1 | 0 10 V | 0 10 V | - |
| R414011410 | G 1 | 4 20 mA | 4 20 mA | - |
| R414011413 | G 1 | - | - | IO-Link |
| R414011415 | G 3/4 | 0 20 mA | 0 10 V | - |
| R414011416 | G 3/4 | 4 20 mA | 4 20 mA | - |
| R414011419 | G 3/4 | - | - | IO-Link |

Page 10 | AVENTICS



The min. control pressure must be adhered to, since otherwise faulty switching and valve failure may result!

The pressure dew point must be at least 15 °C under ambient and medium temperature and may not exceed 3 °C .

The oil content of compressed air must remain constant during the life cycle.

Use only the approved oils from AVENTICS. Further information can be found in the "Technical information" document (available in the MediaCentre).


Power outage: maintain pressure

Technical information

| Material | |
|------------|--------------------------|
| Housing | Polyamide |
| Base plate | Aluminum |
| Seals | Nitrile butadiene rubber |

Dimensions


Dimensions



1) Connection thread

EMERSON


Pressure supply, left



EMERSON

Diagrams

Flow characteristic curve




p1 = Working pressure

p2 = Secondary pressure

qn = Nominal flow

Circuit diagram

Characteristic curve and plug assignment for IO-Link version




1) power supply

2) C/Q Line (pin 4) Not connected (NC) (pin 2) are related to 0 V (pin 3).

3) The power supply must be protected by an external M 0.5 A fuse.



Characteristic and pin assignment for current control with actual output value



1) power supply


2) Actual value (pin 4) and nominal value (pin 2) are related to 0 V (pin 3).

Nominal input value (ohmic load 100 Ω), actual output value: external ohmic load 300 Ω . If the power supply is switched off, the nominal input value is high-ohmic.

3) The power supply must be protected by an external M 0.5 A fuse.

Connect the plug via a shielded cable to ensure EMC.

Characteristic and pin assignment for voltage control with actual output value



1) power supply


2) Actual value (pin 4) and nominal value (pin 2) are related to 0 V (pin 3).

Nominal input value (R = 1 M Ω), actual output value: min. load resistance > 10 K Ω . If the power supply is switched off, the nominal input value is high-ohmic.

3) The power supply must be protected by an external M 0.5 A fuse.



Functional diagram




a) Voltage supply

b) Nominal value

c) Actual output value

Functional diagram, IO-Link




a) Supply Voltage

b) C/Q Line

Pin assignments

Plug assignment



1) 24 V DC

- 2) Nominal input value
- 3) GND
- 4) Actual output value

5) Ground






Round plug connector, Series CON-RD

- Socket, M12x1, 5-pin, A-coded, angled, 90°

- for CANopen
- UL (Underwriters Laboratories)
- shielded



| Connection type | Screws |
|-------------------------------|------------|
| Ambient temperature min./max. | -40 85 °C |
| Operational | 48 V AC/DC |
| voltage | |
| Protection class | IP67 |
| Weight | 0.072 kg |



Technical data

| Part No. | Max. current | suitable cable-Ø min./max |
|------------|--------------|---------------------------|
| 1824484029 | 4 A | 6 / 8 mm |

Technical information


The specified protection class is only valid in assembled and tested state.

| Material | |
|----------|---------------|
| Housing | Die cast zinc |

Page 17 | AVENTICS




Dimensions



Pin assignments

Pin assignment, socket







Round plug connector, Series CON-RD

- Socket M12x1 5-pin A-coded angled 90°
- open cable ends
- with cable
- shielded



| Ambient temperature min./max. | -25 80 °C |
|-------------------------------|-----------------|
| Operational | 48 V AC/DC |
| voltage | |
| Protection class | IP67 |
| Wire cross-section | 0.34 mm² |
| Weight | See table below |

| 1) | BN |
|-----|------|
| 2 > | WH |
| 3 > | ви |
| 4 > | — вк |
| 5) | GY |

Technical data

| Part No. | Max. current | Number of wires | Cable-Ø | Cable length | Weight |
|------------|--------------|-----------------|---------|--------------|----------|
| R419800109 | 4 A | 5 | 6 mm | 2.5 m | 0.145 kg |
| R419800110 | 4 A | 5 | 6 mm | 5 m | 0.27 kg |
| R419800546 | 4 A | 5 | 6 mm | 10 m | 0.514 kg |


| Material | |
|--------------|-------------------------|
| Housing | Thermoplastic elastomer |
| Cable sheath | Polyurethane |



AVENTICS

Dimensions


Dimensions



L = length

Pin assignments

Pin assignment, socket



BN=brown
WH=white
BU=blue
BK=black
GY=grey

Efficient pneumatic solutions, our program: cylinders and drives, valves and valve systems, air supply management



Visit us: Emerson.com/Aventics

Your local contact: Emerson.com/contactus

- C Emerson.com
 - Facebook.com/EmersonAutomationSolutions
- in LinkedIn.com/company/Emerson-Automation-Solutions
 - Twitter.com/EMR_Automation

An example configuration is depicted on the title page. The delivered product may thus vary from that in the illustration. Subject to change. This Document, as well as the data, specifications and other information set forth in it, are the exclusive property of AVENTICS GmbH. It may not be reproduced or given to third parties without its consent. Only use the AVENTICS products shown in industrial applications. Read the product documentation completely and carefully before using the product. Observe the applicable regulations and laws of the respective country. When integrating the product. No statements concerning a certain condition or suitability for a certain application can be derived from our information. The information given does not release the user from the obligation of own judgment and verification. It must be remembered that the products are subject to a natural process of wear and aging.

The Emerson logo is a trademark and service mark of Emerson Electric Co. Brand logotype are registered trademarks of one of the Emerson family of companies. All other marks are the property of their respective owners. © 2017 Emerson Electric Co. All rights reserved. 2019-03



CONSIDER IT SOLVED